

WHAT IS CLAIMED IS:

1. A gain control circuit, comprising:

a transmission power amplifier which amplifies  
a transmission signal to a predetermined level;

5 an adjacent channel leak power ratio monitor which  
finds a ratio of a distortion element corresponding to  
adjacent channel leak power to a main element from  
an output signal of the transmission power amplifier,  
and outputs the found ratio as an ACPR monitor value;

10 a power supply control section which variably  
controls power supply to the transmission power  
amplifier with use of the ACPR monitor value supplied  
from the adjacent channel leak power ratio monitor; and

15 a transmission signal level variable section  
which varies a level of the transmission signal by  
controlling a gain of a transmission signal path on the  
basis of a transmission level monitor value supplied  
from the adjacent channel leak power ratio monitor.

20 2. The circuit according to claim 1, wherein the  
transmission signal level variable section includes:

a variable gain amplifier provided in the transmission  
signal path; and a comparator which compares the  
transmission level monitor value supplied from the  
adjacent channel leak power ratio monitor to a gain  
25 setting value supplied from a base band signal  
processing section, and supplies the result of the  
comparison performed through the comparator to the

1005735.030102

variable gain amplifier as a variable gain control signal.

3. The circuit according to claim 1, wherein the adjacent channel leak power ratio monitor comprises: a  
5 squaring circuit which squares an output signal of the transmission power amplifier; a first band path filter which extracts a distortion element corresponding to the adjacent channel leak power from an output signal of the squaring circuit; a second band path filter  
10 which extracts an element corresponding to a main part of the output signal of the squaring circuit; and a subtracter which performs a subtraction process between an output of the first band path filter and an output of the second band path filter.

4. The circuit according to claim 3, wherein  
15 the squaring circuit includes a multi-plier which multiplies at least two signals together.

5. The circuit according to claim 3, wherein the squaring circuit includes a non-linear device having  
20 a second-order distortion coefficient.

6. A radio communication terminal comprising  
a radio transmission section, wherein  
the radio transmission section comprising:  
a transmission power amplifier which amplifies  
25 a transmission signal to a predetermined level;  
an adjacent channel leak power ratio monitor which finds a ratio of a distortion element corresponding to

10085735.030102

adjacent channel leak power to a main element from  
an output signal of the transmission power amplifier,  
and outputs the found ratio as an ACPR monitor value;

5 a power supply control section which variably  
controls power supply to the transmission power  
amplifier with use of the ACPR monitor value supplied  
the adjacent channel leak power ratio monitor; and

10 a transmission signal level variable section  
which varies a level of the transmission signal by  
controlling a gain of a transmission signal path on the  
basis of a transmission level monitor value supplied  
from the adjacent channel leak power ratio monitor.

15 7. The radio communication terminal according to  
claim 6, wherein the transmission signal level variable  
section includes: a variable gain amplifier provided in  
the transmission signal path; and a comparator which  
compares the transmission level monitor value supplied  
from the adjacent channel leak power ratio monitor to  
a gain setting value supplied from a base band signal  
20 processing section, and supplies the result of the  
comparison performed through the comparator to the  
variable gain amplifier as a variable gain control  
signal.

25 8. The radio communication terminal according to  
claim 6, wherein the adjacent channel leak power ratio  
monitor comprises: a squaring circuit which squares  
an output signal of the transmission power amplifier;

10056735.030102

a first band path filter which extracts a distortion element corresponding to the adjacent channel leak power from an output signal of the squaring circuit; a second band path filter which extracts an element corresponding to a main part of the output signal of the squaring circuit; and a subtracter which performs a subtraction process between an output of the first band path filter and an output of the second band path filter.

10           9. The radio communication terminal according to claim 8, wherein the squaring circuit includes a multiplier which multiplies at least two signals together.

15           10. The radio communication terminal according to claim 8, wherein the squaring circuit includes a non-linear device having a second-order distortion coefficient.